




Step-Down LED Driver

Features


- Maximum constant output current: 750mA
- 96% efficiency @ input voltage 12V, 350mA, 3-LED
- 6~30V input voltage range
- Hysteretic PFM improves efficiency at light loading
- Settable output current
- Integrated power switch with 0.45ohm low Rds(on)
- Full protection: Thermal/Start-Up/LED Open-/Short- Circuit
- Only 4 external components required

Small Outline Transistor



GST: SOT-23-6L

Mini Small Outline Package



GMS: MSOP-8L-118mil

Product Description


The MBI6652 is a high efficiency, constant current and step-down DC/DC converter. It is designed to deliver constant current to light up high power LED with only 4 external components. With hysteretic PFM control scheme, MBI6652 improves the efficiency of light loading. The output current of MBI6652 can be programmed by an external resistor and LED dimming can be controlled via pulse width modulation (PWM) through DIM pin. In addition, the start-up function limits the inrush current while the power is switch on. The MBI6652 also features over temperature protection, LED open-circuit protection and LED short-circuit protection to protect IC from being damaged.

Additionally, to ensure the system reliability, the MBI6652 builds thermal protection (TP) function inside. This function protects IC from overheating (165°C) in various application conditions. MBI6652 provides thermal- enhanced packages as well to handle power dissipation more efficiently. MBI6652 is available in SOT23-6L and MSOP-8L packages.

Applications

- Signage and Decorative LED Lighting
- Automotive LED Lighting
- High Power LED Lighting
- Constant Current Source

Typical Application Circuit



C_{IN}: VISHAY, 293D106X9050D2TE3, D case Tantalum Capacitor
 C_{OUT}: VISHAY, 293D106X9050D2TE3, D case Tantalum Capacitor
 L1: GANG SONG, GSDS106C2-680M
 D1: ZOWIE, SSCD206

Figure 1

Functional Diagram






Figure 2

Pin Configuration



GST : SOT-23-6L



GMS:MSOP-8L

Pin Description

| Pin Name | Function |
|-------------|---|
| GND | Ground terminal for control logic and current sink |
| SW | Switch output terminal |
| DIM | Dimming control terminal. If the dimming function is unnecessary, please let this pin open. |
| SEN | Output current sense terminal |
| VIN | Supply voltage terminal |
| NC | No connection |
| Thermal Pad | Power dissipation terminal connected to GND* |

*To eliminate noise influence, the thermal pad is suggested to connect to GND on PCB. In addition, when a heat-conducting copper foil on PCB is soldered with thermal pad, the desired thermal conductivity will be improved.

Maximum Ratings

Operation above the maximum ratings may cause device failure. Operation at the extended periods of the maximum ratings may reduce the device reliability.

| Characteristic | | Symbol | Rating | Unit |
|--|----------|---------------|----------|---------------|
| Supply Voltage | | V_{IN} | 0~33 | V |
| Output Current | | I_{OUT} | 1 | A |
| Sustaining Voltage at DIM pin | | V_{DIM} | 32 | V |
| Sustaining Voltage at SW pin | | V_{SW} | -0.5~33 | V |
| GND Terminal Current | | I_{GND} | 1 | A |
| Power Dissipation (On 4 Layer PCB, $T_a=25^{\circ}C$)* | GST Type | P_D | 0.51 | W |
| Thermal Resistance (By simulation, on 4 Layer PCB)* | | $R_{th(j-a)}$ | 244 | $^{\circ}C/W$ |
| Power Dissipation (On 4 Layer PCB, $T_a=25^{\circ}C$)* | GMS Type | P_D | 3.3 | W |
| Thermal Resistance (By simulation, on 4 Layer PCB)* | | $R_{th(j-a)}$ | 37.53 | $^{\circ}C/W$ |
| Operating Junction Temperature | | $T_{j,max}$ | 125 | $^{\circ}C$ |
| Operating Temperature | | T_{opr} | -40~+85 | $^{\circ}C$ |
| Storage Temperature | | T_{stg} | -55~+150 | $^{\circ}C$ |

*The PCB size is 76.2mm*114.3mm in simulation. Please refer to JEDEC JESD51.

Note: The performance of thermal dissipation is strongly related to the size of thermal pad, thickness and layer numbers of the PCB. The empirical thermal resistance may be different from simulative value. Users should plan for expected thermal dissipation performance by selecting package and arranging layout of the PCB to maximize the capability.

Electrical Characteristics

Test condition: $V_{IN}=12V$, $V_{OUT}=3.6V$, $L1=68\mu H$, $C_{IN}=C_{OUT}=10\mu F$, $T_A=25^{\circ}C$; unless otherwise specified. Please refer to test circuit (a) of Figure 3.)

| Characteristics | Symbol | Condition | Min. | Typ. | Max. | Unit | |
|---|--------------------|--|------|---------|---------|-------------|---|
| Supply Voltage | V_{IN} | - | 6 | - | 30 | V | |
| Supply Current | I_{IN} | $V_{IN}=6V\sim 30V$ | - | 1 | 2 | mA | |
| Output Current | I_{OUT} | - | - | 350 | 750 | mA | |
| Output Current Accuracy | dI_{OUT}/I_{OUT} | $350mA \leq I_{OUT} \leq 750mA$, | - | ± 3 | ± 5 | % | |
| SW Dropout Voltage | V_{SW} | $I_{OUT}=700mA$ | - | 0.315 | - | V | |
| Internal Propagation Delay Time | T_{pd} | - | 100 | 196 | 300 | ns | |
| Efficiency | - | $V_{IN}=12V$, $I_{OUT}=350mA$, $V_{OUT}=10.8V$ | - | 96 | - | % | |
| Input voltage of DIM | “H” level | V_{IH} | - | 3.5 | - | 5 | V |
| | “L” level | V_{IL} | - | 0 | - | 0.5 | V |
| Switch ON Resistance | $R_{ds(on)}$ | $V_{IN}=12V$; refer to test circuit (b) | 0.4 | 0.45 | 0.6 | Ω | |
| Minimum Switch ON Time* | $T_{ON,MIN}$ | - | 100 | 350 | 450 | ns | |
| Minimum Switch OFF Time* | $T_{OFF,MIN}$ | - | 100 | 350 | 450 | ns | |
| Recommended Duty Cycle Range of SW* | D_{sw} | - | 20 | - | 80 | % | |
| Operating frequency | $Freq_{Max}$ | - | 40 | - | 1400 | kHz | |
| CURRENT SENSE | | | | | | | |
| Mean SEN Voltage | V_{SEN} | $V_{IN}=10V$, $V1=1V$, refer to test circuit (c) | 95 | 100 | 105 | mV | |
| THERMAL OVERLOAD | | | | | | | |
| Thermal Shutdown Threshold* | T_{SD} | - | 145 | 165 | 175 | $^{\circ}C$ | |
| Thermal Shutdown Hysteresis* | T_{SD-HYS} | - | 20 | 30 | 40 | $^{\circ}C$ | |
| DIMMING | | | | | | | |
| Duty Cycle Range of PWM Signal Applied to DIM pin | $Duty_{DIM}$ | PWM frequency: 100Hz ~ 1kHz | 1 | - | 100 | % | |

*Guaranteed by Design.

Test Circuit for Electrical Characteristics




Figure 3

Typical Performance Characteristics

Please refer to Typical Application Circuit, $V_{IN}=12V$, $L1=68\mu H$, $C_{IN}=C_{OUT}=10\mu F$, $T_A=25^\circ C$, unless otherwise specified.

1-LED $V_F=3.6V$; 2-LED $V_F=7.2V$; 3-LED $V_F=10.8V$; 4-LED $V_F=14.4V$; 5-LED $V_F=18V$

1. Efficiency vs. Input Voltage at Various LED Cascaded Number

Efficiency vs. input voltage @ $L1=22\mu H$




Fig 4. $I_{OUT}=715\text{ mA}$




Fig 5. $I_{OUT}=370\text{ mA}$

Efficiency vs. input voltage @ $L1=68\mu H$




Fig 6. $I_{OUT}=715\text{ mA}$




Fig 7. $I_{OUT}=370\text{ mA}$

Efficiency vs. input voltage @ $L1=100\mu H$




Fig 8. $I_{OUT}=715\text{ mA}$




Fig 9. $I_{OUT}=370\text{ mA}$

2. Efficiency vs. LED Cascaded Number at Various Input Voltage

Efficiency vs. LED cascaded number @ L1=22uH




Fig 10. I_{OUT}=715 mA




Fig 11. I_{OUT}= 370 mA

Efficiency vs. LED cascaded number @ L1=68uH




Fig 12. I_{OUT}=715 mA




Fig 13. I_{OUT}=370 mA

Efficiency vs. LED cascaded number @ L1=100uH




Fig 14. I_{OUT}=715 mA




Fig 15. I_{OUT}=370 mA

3. Output Current vs. Input Voltage at Various LED Cascaded Number

Output current vs. input voltage @ L1=22uH




Fig 16. I_{OUT}=715 mA




Fig 17. I_{OUT}=370 mA

Output current vs. input voltage @ L1=68uH




Fig 18. I_{OUT}=715 mA




Fig 19. I_{OUT}=370 mA

Output current vs. input voltage @ L1=100uH




Fig 20. I_{OUT}=715 mA




Fig 21. I_{OUT}= 370 mA

4. Output Current vs. Input Voltage at Various Inductor

Output current vs. input voltage @ 1-LED in cascaded




Fig 22. I_{OUT}=715 mA




Fig 23. I_{OUT}=370 mA

Output current vs. input voltage @ 2-LED in cascaded




Fig 24. I_{OUT}=715 mA




Fig 25. I_{OUT}=370 mA

Output current vs. input voltage @ 3-LED in cascaded




Fig 26. I_{OUT}=715 mA




Fig 27. I_{OUT}=370 mA

5. Output Current vs. LED Cascaded Number at Various Input Voltage

Output current vs. LED cascaded number @ L1=22uH




Fig 28. I_{OUT}=715 mA




Fig 29. I_{OUT}=370 mA

Output current vs. LED cascaded number @ L1=68uH




Fig 30. I_{OUT}=715 mA




Fig 31. I_{OUT}=370 mA

Output current vs. LED cascaded number @ L1=100uH




Fig 32. I_{OUT}=715 mA




Fig 33. I_{OUT}=370 mA

6. Output Current vs. LED Cascaded Number at Various Inductor

Output current vs. LED cascaded number @ VIN=12V




Fig 34. I_{OUT}=715 mA




Fig 35. I_{OUT}=370 mA

Output current vs. LED cascaded number @ VIN=24V




Fig 36. I_{OUT}=715 mA




Fig 37. I_{OUT}=370 mA

Output current vs. LED cascaded number @ VIN=30V




Fig 38. I_{OUT}=715 mA




Fig 39. I_{OUT}=370 mA

7. Switching Frequency vs. LED Cascaded Number at Various Inductor

Switching frequency vs. LED cascaded number @ $V_{IN}=12V$




Fig 40. $I_{OUT}=715\text{ mA}$




Fig 41. $I_{OUT}=370\text{ mA}$

Switching frequency vs. LED cascaded number @ $V_{IN}=24V$




Fig 42. $I_{OUT}=715\text{ mA}$




Fig 43. $I_{OUT}=370\text{ mA}$

Switching frequency vs. LED cascaded number @ $V_{IN}=30V$




Fig 44. $I_{OUT}=715\text{ mA}$




Fig 45. $I_{OUT}=370\text{ mA}$

8. Miscellaneous

(a) Dimming and switching waveforms




Fig 46. Dimming waveform
($V_{IN}=12V$, $R_{SEN}=0.27$, 2-LED)




Fig 47. Switching waveform
($12V_{IN}$, $3.6V_{OUT}$, $R_{SEN}=0.27$)

(b) Line transient response

Line transient response @ $V_{IN}=13V \leftrightarrow 24V$, $V_{OUT}=10V$, $R_{SEN}=0.27$




Fig 48. $L1=22\mu H$




Fig49. $L1=68\mu H$




Fig 50. $L1=100\mu H$

(c) Power supply hot plug-in waveforms




Fig 51. $C_{IN}=C_{OUT}$ =Tantalum capacitor (10uF/50V)




Fig 52. $C_{IN}=C_{OUT}$ =Ceramic capacitor (2 x 4.7uF/35V)

(d) LED hot plug-in waveforms




Fig 53. $C_{IN}=C_{OUT}$ =Tantalum capacitor (10uF/50V)




Fig 54. $C_{IN}=C_{OUT}$ =Ceramic capacitor (2 x 4.7uF/35V)

(e) Internal Propagation Delay Time




Fig 55




Fig 56

Application Information

The MBI6652 is a simple and high efficient buck converter with capability to drive up to 750mA of loading. The MBI6652 adopts hysteretic PFM control scheme to regulate loading and input voltage variations. The hysteretic PFM control requires no loop compensation bringing very fast load transient response and achieving excellent efficiency at light loading.

Setting Output Current

The output current (I_{OUT}) is set by an external resistor, R_{SEN} . The relationship between I_{OUT} and R_{SEN} is as below;

$$V_{SEN}=0.1V;$$

$$R_{SEN}=(V_{SEN}/I_{OUT})=(0.1V/I_{OUT});$$

$$I_{OUT}=(V_{SEN}/R_{SEN})=(0.1V/R_{SEN})$$

where R_{SEN} is the resistance of the external resistor connecting to SEN terminal and V_{SEN} is the voltage of external resistor. The magnitude of current (as a function of R_{SEN}) is around 700mA at 0.143Ω.

Minimum Input Voltage and Start-up Protection

The minimum input voltage is the sum of the voltage drops on R_{SEN} , R_S , DCR of L1, $R_{ds(on)}$ of internal MOSFET and the total forward voltage of LEDs. The dynamic resistance of LED, R_S , is the inverse of the slope in linear forward voltage model for LED. This electrical characteristic can be provided by LED manufacturers. The equivalent impedance of the MBI6652 application circuit is shown in Figure 57. As the input voltage is smaller than minimum input voltage such as start-up condition, the output current will be larger than the preset output current. Thus, under this circumstance, the output current is limited to 1.15 times of preset one as shown in Figure 58.





Figure 58. The start-up waveform @ $V_{IN}=12V$, $V_{OUT}= 10.8$, $R_{SEN}=0.27$

Figure 57. The equivalent impedance in a MBI6652 application circuit

Dimming

The dimming of LEDs can be performed by applying PWM signals to DIM pin. A logic low (below 0.5V) at DIM will disable the internal MOSFET and shut off the current flow to the LED array. An internal pull-up circuit ensures that the MBI6652 is ON when DIM pin is unconnected. Therefore, the need for an external pull-up resistor will be eliminated. The following Figure 59 and 60 show good linearity in dimming application of MBI6652.




Figure 59. DIM duty cycle: 1% ~ 100%




Figure 60. DIM duty cycle: 1% ~ 10%

LED Open-Circuit Protection

When any LED connecting to the MBI6652 is open-circuited, the output current of MBI6652 will be turned off. The waveform is shown in Figure 61.




Figure 61. Open-circuit protection

LED Short-Circuit Protection

When any LED connecting to the MBI6652 is short-circuited, the output current of MBI6652 will still be limited to its preset value as shown in Figure 62.




Figure 62. Short-circuit protection

TP Function (Thermal Protection)

When the junction temperature exceeds the threshold, T_x (165°C), TP function turns off the output current. The waveform can refer to Figure 63. The SW stops switching and the output current will be turned off. Thus, the junction temperature starts to decrease. As soon as the temperature is below 135°C, the output current will be turned on again. The switching of on-state and off-state are at a high frequency thus the blinking is imperceptible. The average output current is limited and therefore, the driver is protected from being overheated.




Figure 63. Thermal protection

Design Consideration

Switching Frequency

To achieve better output current accuracy, the switching frequency should be determined by minimum on/off time of SW waveform. For example, if the duty cycle of MBI6652 is larger than 0.5, then the switching frequency should be determined by the minimum off time, and vice versa. Thus the switching frequency of MBI6652 is:

$$f_{sw} = \frac{1}{T_s} = \frac{1}{\frac{T_{OFF,min}}{(1-D)}} , \text{ when the duty cycle is larger than 0.5} \tag{1}$$

$$\text{or } f_{sw} = \frac{1}{T_s} = \frac{1}{\frac{T_{ON,min}}{D}} , \text{ when the duty cycle is smaller than 0.5.} \tag{2}$$

The switching frequency is related to efficiency (better at low frequency), the size/cost of components (smaller/ cheaper at high frequency), and the amplitude of output ripple voltage and current (smaller at high frequency). The slower switching frequency comes from the large value of inductor. In many applications, the sensitivity of EMI limits the switching frequency of MBI6652. The switching frequency can be ranged from 40kHz to 1.4MHz.

LED Ripple Current

A LED constant current driver, such as MBI6652, is designed to control the current through the cascaded LED, instead of the voltage across it. Higher LED ripple current allows the use of smaller inductance, smaller output capacitance and even without an output capacitor. The advantages of higher LED ripple current are to minimize PCB size and reduce cost because of no output capacitor. Lower LED ripple current requires larger inductance, and output capacitor. The advantages of lower LED ripple current are to extend LED life time and to reduce heating of LED. The recommended ripple current is from 5% to 20% of normal LED current.

Component Selection

Inductor Selection

The inductance is determined by two factors: the switching frequency and the inductor ripple current. The calculation of the inductance, L1, can be described as

$$L1 > (V_{IN} - V_{OUT} - V_{SEN} - (R_{ds(on)} \times I_{OUT})) \times \frac{D}{f_{SW} \times \Delta I_L}$$

where

$R_{ds(on)}$ is the on-resistance of internal MOSFET of the MBI6652. The typical is 0.45Ω at 12V_{IN}.

D is the duty cycle of the MBI6652, $D=V_{OUT}/V_{IN}$.

f_{SW} is the switching frequency of the MBI6652.

I_L is the ripple current of inductor, $I_L=(1.15 \times I_{OUT})-(0.85 \times I_{OUT})=0.3 \times I_{OUT}$.

When selecting an inductor, not only the inductance but also the saturation current that should be considered as the factors to affect the performance of module. In general, it is recommended to choose an inductor with 1.5 times of LED current as the saturation current. Also, the larger inductance gains the better line/load regulation. However, the inductance and saturation current become a trade-off at the same inductor size. An inductor with shield is recommended to reduce the EMI interference, however, this is another trade-off with heat dissipation.

Schottky Diode Selection

The MBI6652 needs a flywheel diode, D1, to carry the inductor current when the MOSFET is off. The recommended flywheel diode is schottky diode with low forward voltage for better efficiency. Two factors determine the selection of schottky diode. One is the maximum reverse voltage. The recommended rated voltage of the reverse voltage is at least 1.5 times of input voltage. The other is the maximum forward current, which works when the MOSFET is off. And the recommended forward current is 1.5 times of output current. Users should carefully choose an appropriate schottky diode which can perform low leakage current at high temperature.

Input Capacitor Selection

The input capacitor, C_{IN}, can supply pulses of current for the MBI6652 when the MOSFET is ON. And C_{IN} is charged by input voltage when the MOSFET is OFF. As the input voltage is lower than the tolerable input voltage, the internal MOSFET of the MBI6652 remains constantly ON, and the LED current is limited to 1.15 times of normal current. The recommended value of input capacitor is 10uF to stabilize the lighting system.

The rated voltage of input capacitor should be at least 1.5 times of input voltage. A tantalum or ceramic capacitor can be used as an input capacitor. The advantages of tantalum capacitor are high capacitance and low ESR. The advantages of ceramic capacitor are high frequency characteristic, small size and low cost. Due to low ESR characteristic of ceramic capacitor, please do not use hot plugging. Users can choose an appropriate one for their applications.

Output Capacitor Selection (Optional)

A capacitor paralleled with cascaded LED can reduce the LED ripple current and allow smaller inductance.

PCB Layout Consideration

To enhance the efficiency and stabilize the system, careful considerations of PCB layout is important. There are several factors should be considered.

1. A complete ground area is helpful to eliminate the switching noise.
2. Keep the IC's GND pin and the ground leads of input and output filter capacitors less than 5mm.
3. To maximize output power efficiency and minimize output ripple voltage, use a ground plane and solder the IC's GND pin directly to the ground plane.
4. To stabilize the system, the heat sink of the MBI6652 is recommended to connect to ground plane directly.
5. Enhance the heat dissipation, the area of ground plane, which IC's heat sink is soldered on, should be as large as possible.
6. The input capacitor should be placed to IC's VIN pin as close as possible.
7. To avoid the parasitic effect of trace, the R_{SEN} should be placed to IC's VIN and SEN pins as close as possible.
8. The area, which is composed of IC's SW pin, schottky diode and inductor, should be wide and short.
9. The path, which flows large current, should be wide and short to eliminate the parasite element.
10. When SW is ON/OFF, the direction of power loop should keep the same way to enhance the efficiency. The sketch is shown as Figure 64.




Figure 64. Power loop of MBI6652

PCB Layout







Figure 65. The layout diagram of the MBI6652 GMS

Package Power Dissipation (PD)


The maximum power dissipation, $P_D(max)=(T_j-T_a)/R_{th(j-a)}$, decreases as the ambient temperature increases.



Outline Drawing



MBI6652 GST Outline Drawing




MBI6652 GMS Outline Drawing

Note1: The unit for the outline drawing is mm.


Note2: Please use the maximum dimensions for the thermal pad layout. To avoid the short circuit risk, the vias or circuit traces shall not pass through the maximum area of thermal pad.

Product Top Mark Information

GST



GMS



Product Revision History

| | |
|-------------------|---------------------|
| Datasheet version | Device Version Code |
| V1.00 | A |

Product Ordering Information

| Part Number | “Pb-free” Package Type | Weight (g) |
|-------------|------------------------|------------|
| MBI6652GST | SOT-23-6L | 0.016g |
| MBI6652GMS | MSOP-8L | 0.0233g |

Disclaimer

Macroblock reserves the right to make changes, corrections, modifications, and improvements to their products and documents or discontinue any product or service. Customers are advised to consult their sales representative for the latest product information before ordering. All products are sold subject to the terms and conditions supplied at the time of order acknowledgement, including those pertaining to warranty, patent infringement, and limitation of liability.

Macroblock's products are not designed to be used as components in device intended to support or sustain life or in military applications. Use of Macroblock's products in components intended for surgical implant into the body, or other applications in which failure of Macroblock's products could create a situation where personal death or injury may occur, is not authorized without the express written approval of the Managing Director of Macroblock. Macroblock will not be held liable for any damages or claims resulting from the use of its products in medical and military applications.

All text, images, logos and information contained on this document is the intellectual property of Macroblock.

Unauthorized reproduction, duplication, extraction, use or disclosure of the above mentioned intellectual property will be deemed as infringement.